

Seymour Duncan®

Unpacking

Inspect your Convertible™ amp for hidden damage that may have occurred in transit. Your amp was inspected and sound tested before shipment from the factory.

All claims for shipping damage must be made by the receiver. Save your box and packing material for evidence of damage if it has occurred.

Packing Materials

The original box and packing materials are specially designed to protect your amp during shipment. **SAVE ALL PACKING MATERIALS.** In the unlikely event that your amp needs to be returned to the factory, the original box and packing material will be necessary for shipment. These are carrier approved packing materials and they will insure safe transit back to the factory.

Specifications for 100 watt Convertible Amps

	Combo	Head
Weight:	57 lbs	42 lbs
Cabinet Dimensions:	19 3/4" h	10 15/16" h
	18 25/32" w	21 25/32" w
	11 3/8" d	11 1/16" d
Power Requirements:	120 volts a.c. (U.S. models)	
Power Consumption:	480 watts at full rated output.	
Power Circuit:	All tube, EL-34 tubes	
	100 watt rms @ 8	
	ohms from 8 ohm out-	
	put @ 120 v.a.c. @ 5%	
Damping Factor:	@ 1 khz.	
	From damping output: Low - 0.1 into 4 ohms;	
	High - 4.0 into 8 ohms	
Input Impedance:	4.7 meg-ohms adjustable to zero via load resistor plugs.	
Input Sensitivity:	(with Normal, Normal, Normal modules): 1.2 millivolts.	
Dynamic Headroom:	4-5 db	